

## CM series (4 – 10 A) Solar Charge Controllers

- Charging display with LED
  Large terminals (up to 16mm<sup>2</sup>)
- PWM-regulation
- Boost & float charging method
- Solid-state overvoltage protection
- Reverse polarity protection

The CM charge controller is especially for use in small solar systems where no load disconnect is required, as in yachts, caravans, etc.

The charging regime provides best battery treatment at reasonable cost. The electronic circuit is equipped with a microcontroller that provides high-efficiency charging technology.

Туре	CM 04	CM 10	
System voltage	12 V		
Max. charge current	4 A	10 A	
Float charge	13.7 V		
Boost charge	14.5 V		
	activation: battery voltage < 12.2 V		
Max. panel voltage	30 V		
(Overvoltage protection by varistor)			
Max. self consumption	4 mA		
Grounding	positive grounding possible		
Ambient temperature	-40 to +50 °C		
Max. height	4,000 m above sea level		
Battery type	lead acid (GEL, AGM, flooded)		
Wire cross section	< 16 mm <sup>2</sup>		
Weight	68 g		
Dimensions (W x H x D)	72.6 x 61 x 30.4 mm		
Type of protection	IP22		

Datasheet\_CM series\_1/1\_e\_2010-04-01\_Subject to change without notice

 Phocos AG
 Tel. +49 731 9380688-0

 Magirus-Deutz-Str. 12
 Tel. +49 731 9380688-0

 89077 Ulm, Deutschland
 Fax +49 731 9380688-50